



Off-Grid Inverter
with Charger

Argon Series

Operation without battery



Intelligent Load
Management



Batteryless
Operation



Battery managemnt
system

Models:

Argon VM II 1500
Argon VM II 2500

Argon VM II 3000
Argon VM II 5500



Easy-to-install

- Pure sine wave solar inverter
- Reserved communication port for BMS
- Wide PV input range



Reliable

- Battery independent design
- Maximum charging current 100A
- Built-in anti-dust kit



User-friendly

- Battery equalization function to optimize battery performance and extend lifecycle

MODEL	Argon VM II 1500	Argon VM II 2500	Argon VM II 3000	Argon VM II 5500
Rated Power	1200VA/1200W	2500VA/2500W	3000VA/3000W	5000VA/5000W
INPUT				
Voltage	230 VAC			
Selectable Voltage Range	170-280 VAC (For Personal Computers) ; 90-280 VAC (For Home Appliances)			
Frequency Range	50 Hz/60 Hz (Auto sensing)			
OUTPUT				
AC Voltage Regulation (Batt. Mode)	230VAC ± 5%			
Surge Power	2400VA	5000VA	6000VA	10000VA
Efficiency (Peak)	93%			
Transfer Time	10 ms (For Personal Computers) ; 20 ms (For Home Appliances)			
Waveform	Pure sine wave			
BATTERY				
Battery Voltage	12 VDC	24 VDC		48 VDC
Floating Charge Voltage	13.5 VDC	27 VDC		54 VDC
Overcharge Protection	16 VDC	32 VDC		63 VDC
SOLAR CHARGER & AC CHARGER				
Solar Charger Type	MPPT			
Maximum PV Array Open Circuit Voltage	350 VDC	450 VDC		500 VDC
Maximum PV Array Power	1500W	3000W	3500W	5500W
MPP Range @ Operating Voltage	60 ~ 300 VDC	60 ~ 400 VDC		120 ~ 450VDC
Maximum Solar Charge Current	100 A			100A
Maximum AC Charge Current	80A			100A
Maximum Charge Current	100A			100A
PHYSICAL				
Dimension, D x W x H (mm)	90 x 288 x 357		110 x 288 x 390	120 x 300 x 440
Net Weight (kgs)	6.5	7.0	7.2	10
Communication Interface	RS232/RS485, optional WiFi			
ENVIRONMENT				
Humidity	5% to 95% Relative Humidity (Non-condensing)			
Operating Temperature	-10°C to 50°C			
Storage Temperature	-15°C to 60°C			